

LINN MAJIK

Sophisticated control amplifier complete with on-board stereo power amplifiers. A core entry-level product for powerful and flexible control of hi-fi, video or multi-room installations.

“Sneaky” add-on modules expand its functions.

- As a preamplifier the Majik accommodates many source components
- Available in two versions, one with five line-level inputs and switchable phono input. The second version with six line-level inputs
- Microprocessor controlled electronic switching for superior performance and reliability with no sonic degradation over time
- Ultra-short paths to preserve music signal integrity
- Headphone socket on front facia
- Power amplifier section powerful enough to drive virtually any loudspeaker, which also accommodates Linn active loudspeaker crossover modules
- Can be fitted with ‘Sneaky Kudos’ tuner module to operate receiver
- Can be fitted with ‘Sneaky’ Knekt Line Driver or Local Receiver modules to integrate with multi-room systems to distribute sound from a primary location or to control a playback system in a secondary room

Introduction:	1993
Type:	Control Amplifier
Connectors:	Gold-plated RCA Phono
Audio Inputs:	Levels (for 40mV rms line output at 1k Hz at maximum gain); MC: 250uV/150 Ohms/10nF; MM: 2mV/47k Ohms//68pF; Tuner, CD, Aux: 300mV/10k Ohms; Tape 1 & 2 188mV/10k Ohms; Line-level version substitutes phono inputs with an extra Auxilliary input
Audio Line Output:	Max Output Level: 6Vrms; Impedance: 200 Ohms; Minimum Load: 1k Ohm
Power Amplifier Section:	Input Impedance: 10k Ohms; Voltage Gain: 28.5dB; Power Output: 66W/Channel/4 Ohms, 33W/Channel/8 Ohms
Speaker Connectors:	4 pairs 4mm sockets/channel
Power Consumption:	320W maximum, 25W idling
Mains Supply:	100/120/220/240V +/- 10%
Size:	W 320MM X D 326MM X H 80MM
Weight:	4.9kg