



LINN

KEY FEATURES INCLUDE

- I Linn's patented "Switch Mode Power Supply" ensures that power delivery is smooth and clean at all times
- I Automatic on/off signal sensing circuitry detects the presence of an audio signal, and reverts to standby when the signal is absent
- I Switchable voltage ranges for worldwide operation
- I 230W power output into 4 ohms
- I Accepts internal Stereo AKTIV cards
- I Bi-wireable loudspeaker outputs
- I Additional line out for daisy-chaining channels

The 2250 power amplifier from Linn is a high-powered amplifier designed for AV and audio applications where premium sound quality matters. Similar in size and styling to Linn's successful 5125 power amplifier, the 2250 amplifier offers an improved level of performance, optimised for 2-channel stereo.

The product also features Linn's "Switch Mode Power Supply" to ensure that the delivery of power is smooth, clean and always silent. As with all other Linn amplifiers, the 2250 features signal sensing circuitry which enables the amplifier to revert to standby when not in use, thereby reducing power consumption.

This amplifier represents a flexible solution for those who wish to upgrade their home entertainment systems, either through an improvement in current sound performance or through the addition of extra channels. It can be used as a modular 'building block' product for users looking to build a high-quality audio or AV system, and offers added performance benefits through the optional inclusion of Linn's AKTIV cards.

Available in both Black and Silver finishes, the 2250 power amplifier delivers a very high level of performance which belies its price tag.

## 2250 POWER AMPLIFIER

### SPECIFICATION

A versatile, high performance two channel power amplifier for high-quality AV and audio applications



1



2



3

# 2250 POWER AMPLIFIER

## TECHNICAL SPECIFICATION

A versatile, high performance two channel power amplifier  
for high-quality AV and audio applications

### Input connectors

I	Unbalanced (switch position in)	WBT phono socket
I	Balanced (switch position out)	XLR socket
I	Pin connections	Phono; Inner: Hot (+), Outer: 0V XLR; Pin 1: 0V, Pin 2: Hot (+), Pin 3: Cold (-)

### Gain

I	Unbalanced	28.3dB
I	Balanced	22.3dB

### Input impedance

I	Unbalanced	7K8ohms
I	Balanced	7K8ohms

### Input level for clipping

I	Unbalanced	1.2V rms
I	Balanced	2.4V rms
I	Signal sensing threshold	>150uV

I	Output power	230W rms into 4ohms 115W rms into 8ohms
---	--------------	--------------------------------------------

I	Load tolerance	Unconditionally stable into all loudspeaker loads
---	----------------	------------------------------------------------------

I	Harmonic distortion	<0.02%
I	Frequency response	7Hz to 35kHz (-3dB)
I	Peak output voltage	45V

### Protection

I	Fuse rating	T6.3AL
I	Mains input range	100Vac - 120Vac @ 50/60Hz +/-10% 220Vac - 240Vac @50/60Hz +/-10%
I	Maximum input power	1000W
I	Typical operating input power	44W
I	Standby power	15W
I	Dimensions	H 75mm x W 381mm x D 354mm H 2.9 inches x W 15 inches x D 13.9 inches
I	Weight	5.25kg (11.6lbs)

The above information is subject to change without prior notice

Linn Products Limited  
Floors Road, Waterfoot, Glasgow G76 0EP, Scotland, UK.  
Telephone: +44 (0) 141 307 7777, Facsimile: +44 (0) 141 644 4262, Helpline: 0500 888909, E-mail: [helpline@linn.co.uk](mailto:helpline@linn.co.uk), Website: [www.linn.co.uk](http://www.linn.co.uk)

Linn Products Inc  
8787 Perimeter Park Boulevard, Jacksonville FL 32216, USA.  
Telephone: +1 (904) 645 5242, Facsimile: +1 (904) 645 7275, Helpline: 888-671-LINN, E-mail: [helpline@linninc.com](mailto:helpline@linninc.com), Website: [www.linninc.com](http://www.linninc.com)

Linn Deutschland GmbH  
Albert-Einstein-Ring 19, 22761 Hamburg, Deutschland.  
Telephone: +49-40-890 660-0, Facsimile: +49-40-890 660-29, Helpline: 0800 8221560, E-mail: [info@linngmbh.de](mailto:info@linngmbh.de), Website: [www.linn.co.uk](http://www.linn.co.uk)

Linn Records Ltd  
257 Drakemire Drive, Castlemilk, Glasgow G45 9SZ, Scotland, UK.  
Telephone: +44 (0) 141 303 5027, Facsimile: +44 (0) 141 634 0733, Helpline/Mail order: +44 (0) 141 303 5029, E-mail: [records@linn.co.uk](mailto:records@linn.co.uk),  
Website: [www.linnrecords.com](http://www.linnrecords.com)

Pack 786 (First Printed July 2002)