



MAJIK DS-I QUICKSTART

Thank you for purchasing the Linn Majik DS-I player. This guide provides basic unpacking and connecting information to get you started - contact your Linn Specialist for full installation support.

IMPORTANT:

Please refer to the printed Safety Information booklet for important safety information and the online manual available at www.linn.co.uk/majikdsi for full instructions on using your Linn Majik DS-I player.

Unpacking

- Remove product from packaging and place on a flat surface
- Please retain all packaging for future transport of Majik DS-I

Contents

- 1 x Majik DS-I player
- 1 x mains lead
- 1 x luminous infra-red (IR) handset (with 2 x AAA batteries)
- 1 x Safety Information booklet

Positioning

- Place unit on a flat, stable and rigid surface
- Place unit within range of your network router or switch


IMPORTANT:

Linn recommend the use of separate dedicated network components, including router, switch and wireless access point (if required for wireless control). Alternatively, a dedicated integrated router/switch/wireless device is preferable to simply connecting the unit directly to your home broadband router. Linn do not recommend a wireless connection between DS player and network. See www.linn.co.uk/networks for more info

- Avoid positioning the unit in direct sunlight as this can interfere with the infra-red (IR) sensor on the front panel
- Do not stack components and avoid placing near other heat sources
- Do not block vents or site the unit in a cabinet which prevents air flowing from front to back
- Allow at least 4" (10 cm) all the way around the unit for air circulation

Connecting

1. Connect each left and right channel on the Majik DS-I to the equivalent terminal on your loudspeaker using your preferred connection method (spade / banana plug / bare wire) and ensuring a good tight connection is made in each case
2. Connect the Majik DS-I Ethernet socket to your network using a standard Ethernet cable




3. Connect any additional source components to the back panel using your preferred connection method (phono or balanced) - use socket **4/PH** for any turntable you wish to connect (and **do not connect** line level source components to this socket)
- Your Majik DS-I is configured as an MM (Moving Magnet) phono stage as default - please contact your Linn Specialist if you wish to change this to MC (Moving Coil) or convert socket **4/PH** to line level
4. Connect your mains cable but do not power on the unit yet
5. If you have a NAS or ripping NAS then you should also ensure this is connected to your network and powered on (see www.linn.co.uk/nas for more info)

Setup

Step 1 - add Majik DS-I to network

- 1.1 Connect the Majik DS-I as shown overleaf and power the unit on using the switch on the rear of the unit
- 1.2 The Majik DS-I should display a flashing blue dot for several seconds before changing to a Linn logo



- 1.3 Press the **Standby** button to come out of standby mode - if you have a large X displayed on the front panel then there is no active network connection

- Go to www.linn.co.uk/networks if you have any problems or questions

Step 2 - run Konfig

- 2.1 Install Linn Konfig on your computer from www.linn.co.uk/konfig
- 2.2 Launch Konfig and confirm that your Majik DS-I is visible
- 2.3 Konfig will also display any media servers or other Linn devices you have connected to the network - if you can't see these devices in Konfig then you will be unable to find music on your NAS etc.
- 2.4 Select your Majik DS-I within Konfig and choose the Configuration tab to begin configuring your sources, including renaming them, changing volume settings and defining a startup source (select Help from Konfig for more info)

- Go to www.linn.co.uk/networks if you have any problems or questions

Step 3 - play music

- 3.1 Install KinskyDesktop on your computer from www.linn.co.uk/kinskydesktop
- 3.2 Launch KinskyDesktop and it will detect any DS players connected to the network and automatically select the first discovered DS player - check the **Rooms** menu - if no Room is available, refer back to *Step 2* above
- 3.3 Select the **Radio** source from the top-right menu and double-click on an internet radio station to play (internet connection required)
- 3.4 Select the **Playlist** source (if you have music files stored on your computer) and go to your computer's music folder and drag any track(s) into your KinskyDesktop playlist and press **Play**
- 3.5 Ensure all connected sources are powered on and play music on each one to confirm correct setup, selecting the appropriate source from the **Sources** menu in KinskyDesktop or using **Source +/-** to change sources on your front panel or remote control handset
- 3.6 **iTunes users** - simply select iTunes from the **Home** page to browse your iTunes library and playlists, and select and play tracks as normal

- Go to www.linn.co.uk/kinskydesktop for a short demo or further help

Step 4 - rip music

- 4.1 If you have a ripping NAS, simply insert the disc and ripping will start automatically (this should take around 5 - 10 minutes and the disc will be ejected once complete)
- 4.2 If you are using a standard (non-ripping) NAS or computer to store your music files, rip your music as normal and ensure you prompt your Media Server to update
 - A Media Server is required to manage your music collection and provide access for your Linn DS player - see www.linn.co.uk/mediaserver for more info
- 4.3 Select **Library** from the **Home** page in KinskyDesktop to view available media servers (e.g. Asset UPnP, Twonky) and double-click on a media server to browse and select music
 - Go to www.linn.co.uk/ripping for more info on ripping music discs, including a beginner's guide to ripping and software recommendations

Step 5 - add wireless device

- 5.1 Simply add a wireless device or smartphone to your network as normal
- 5.2 Download a suitable DS control app for that device
- 5.3 Launch the software on your wireless device and it should auto-detect your DS player and music library, and allow you to select and play tracks
 - Go to www.linn.co.uk/wireless for more info on wireless control of your DS and a list of recommended devices and software - wireless is only recommended by Linn for control of your DS player, not for actual streaming of music

Online Manual

Please visit www.linn.co.uk/majikdsi to view the latest Online Manual for Linn Majik DS-I, which includes full instructions on configuring your network, ripping and downloading music, and controlling your DS player using a range of devices.

Warranty

Please visit www.linn.co.uk/warranty within 30 days of purchase to register your product for an extended 5 year warranty.

Linn Records

Please visit www.linnrecords.com for a selection of recordings available as Studio Master downloads, CD/SACD or 180g vinyl.

Linn Products Limited

Glasgow Road, Waterfoot, Eaglesham,
Glasgow G76 0EQ, Scotland, UK

- Phone: +44 (0)141 307 7777 • Fax: +44 (0)141 644 4262
- Helpline: 0500 888909 • Email: helpline@linn.co.uk
- Website: www.linn.co.uk



LINN